

BatteryMart.com

Dual-voltage, Regulated, Sealed Lead-Acid Battery Chargers

12BC1000D-1

BatteryMart.com's top-of-the-line chargers are designed to maintain maximum performance from your batteries. These chargers feature dual-voltage output, and regulated current control to insure that no damage occurs during charging or while the battery remains on the charger. The charger is provided with screw-terminal outputs, allowing the user to attach any output cable they desire. Cables with various connectors can be supplied by BatteryMart.com at extra cost.

The 12BC1000D-1 charger begins its charge cycle on "fast-charge", providing the battery with constant voltage of 15VDC, and regulated current of 1000mA. This charge cycle is indicated by the red LED. As the charging cycle progresses, the terminal voltage of the battery will rise to an eventual 15VDC. At this point, the charger senses this voltage, and the fast-charge circuit cuts-off, also turning off the red LED. The "float-charge" circuit then comes on along with the green LED, providing the battery with a constant voltage of 13.8VDC. This voltage can be left on the battery indefinitely without damage, and keeps the battery fully charged, ready for use at all times.

PRIMARY	Voltage	120VAC, 60Hz, +/- 15V
	Exciting Current	60mA
	Rated Input Power	25VA
	DC Resistance	40 ohms +/- 10%

OUTPUT:	Float	Fast-Charge
Voltage	13.6-13.8Vdc	14.8-15VDC
Current	50mA	1100mA Max.

INSULATION RESISTANCE	Primary-Secondary	100M ohm @ 500Vdc
	Primary-Core	100M ohm @ 500Vdc
DIELECTRIC STRENGTH	Primary-Secondary	1500Vac for 1 min.
	Primary-Core	1500Vac for 1 min.
	Secondary-Core	1500Vac for 1 min.

TEMPERATURE RISE	Max. 75 Degree C @ rated load
------------------	-------------------------------

RED LED "on":	Charger is in "CHARGING" mode.
GREEN LED "on"	Battery is charged for use, and the "float" charge is operating.